

CLASS BOOSTER 4500



Input Voltage 1Ph 230 Volt
Battery 12 - 24 Volt, 35 > 600 Ah



Description

- Code: 363400

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- **Fast charging with timer**
- **Overload protection**
- **Short circuits protection**
- **Inversions of polarity protection**
- **Manual charge breaker**

Features

Input Voltage (Volt 50-60Hz AC):	1 Ph x 230
Nominal battery voltage (Volt):	12 / 24
Power (KW):	1,7 / 7,5
Average charging current (Amp):	50,0
Effective charging current (Amp):	75,0
Battery capacity (Ah min/max):	35 / 600
Charging positions (N°):	4
Boosting Current (Amp 0 Volt CC):	500
Boosting current (Amp 1 Volt / EL):	330
Weight Kg ≈:	25.5
Dimension, Wid.-Dep.-Height (mm):	470 x 320 x 750
LOGISTIC INFO CODE :	363400
Barcode:	8011399020342
Package dimension, Wid.-Dep.-Height (mm):	685 x 360 x 295
Package weight kg:	26
Pieces for pallet:	15
HS code:	85044055

Optional accessory